



The APart E-VOL120 is a 100Volt volume control that can handle up to 120 Watt of power. It is very versatile thanks to the step-by-step attenuation in 11 steps + zero position.

The E-VOL 120 is designed to handle 24V priority signals. This means that you can always get an announcement out, even to zones where the local volume control is in the 'OFF' position!

If your amplifier has a 24 V priority output, it will send a 24 V signal when you push the talk button on the microphone. The 24 V signal will close a relay on the E-VOL120 volume control, and the signal will pass, even when the volume control is in the 'OFF' position. This can be very useful for emergency or evacuation messages.

The E-VOL120 is built on a universal chassis that easily can be integrated with Gira, Jung and Euro. Different cover plates are available for the UK market.

## TECHNICAL SPECIFICATIONS

Type	Euro
Handling Power	120 Watt
Voltage	100 Volt
24 V priority	Yes
Attenuation steps	11 + "0"
Build-on box	E-MODON
Dimensions (HxWxD)	80 x 80 x 50 mm
Weight	336 grams
color	white